

T/LL36X INSTALLATION INSTRUCTIONS







Model variant table		
Model No	Output	
T/LL360	Resistive	
T/LL361	Voltage	
T/LL362	Current	
T/LL363	Resistive + alarm	
T/LL364	Voltage + alarm	
T/LL365	Current + alarm	

1. System Description:

The T/LL36X consists of a tank mounted electronics enclosure and a twin capacitive probe made from an anodized aluminium extrusion. The sender output is specified by the customer and factory set during manufacture.

2. Output Options:

T/LL360 Emulated resistance # Any range value 3 – 500 Ω or 500 – 3 Ω	T/LL363 Emulated resistance # Any range value 3 $-$ 500 Ω or 500 $-$ 3 Ω With level alarm #
T/LL361 Voltage 0-10 VDC range (24 V systems) 0-5 VDC range (12 V systems). NB max load on voltage output = 10 mA	T/LL364 Voltage 0-10 VDC range (24 V systems) 0-5 VDC range (12 V systems). NB max load on voltage output = 10 mA With level alarm #
T/LL362 Current Any range value 0-20 mA range	T/LL365 Current Any range value 0-20 mA range With level alarm #

NB Level alarm output options - maximum load 100 mA.

3. Mechanical Fixing:

1" BSPT, mounting thread or 5 hole SAE flange mounting. Guide the probe through the tank opening. Either secure the 5 off M5 bolts to a torque of 22 Nm or thread into position on 1" BSPT thread to hand tight plus one quarter turn with a peg spanner

4. Electrical Supply

Voltage Supply: 9-32 VDC

Current Supply: Max 35 mA at 24 VDC

5. Electrical Connections

Electrical connectors are fitted as specified by the customer. For a standard unit, the convention used is:

Red wire: V+, Black wire: Ground (0 V), Green wire: Signal

For units with level alarm: White wire: Alarm switch

Notes:

A minimum clearance of 20 mm between the end of the probe and the bottom of the tank is recommended. # Do not connect V+ supply voltage to the signal or level alarm out pin ~ this may damage the sender electronics.

Hermes Close | Tachbrook Park | Warwick | CV34 6UF | United Kingdom Tel: +44 (0)1926 466700 | Fax: +44 (0)1926 450473 | sales@fozmula.com

www.fozmula.com